TITLE OF THE INVENTION

SEMICONDUCTOR TESTING APPARATUS AND METHOD FOR
OPTIMIZING A WAIT TIME UNTIL STABILIZATION OF
SEMICONDUCTOR DEVICE OUTPUT SIGNAL

5   CROSS-REFERENCE TO RELATED APPLICATIONS

This application is based upon and claims the
benefit of priority from the prior Japanese Patent
Applications No. 2001-012121, filed January 19, 2001;
No. 2001-253233, filed August 23, 2001; and
10   No. 2001-253235, filed August 23, 2001, the entire
contents of all of which are incorporated herein by
reference.

BACKGROUND OF THE INVENTION

1. Field of the Invention

15   The present invention relates to a semiconductor
testing apparatus and semiconductor testing method for
testing a semiconductor device for, for example, a
television, a video tape recorder (VTR), a digital
versatile disk (DVD) and audio application.

20   Further, the present invention relates to
an apparatus and method for optimizing a wait time
involved until an output signal of a semiconductor
device becomes stable in the measurement of the
electrical characteristics of the semiconductor device,
25   such as the voltage, current, waveform, timing, phase,
etc., of the output signal. In particular, the present
invention is used for debugging a semiconductor device.

2. Description of the Related Art

Generally, resin-molded semiconductor device packages and wafer-state semiconductor devices before die-sorting are tested for their electrical characteristics and, based on the results, an OK/NG (OK/No Go) decision is made. When a semiconductor device is tested by the semiconductor testing apparatus for electrical characteristics, the testing apparatus optimizes a wait time involved until an output signal becomes stable. Here, a stable output signal means a state in which data values measured a plurality of times are similar to within a few percent. Therefore, an unstable output signal means a state in which data values measured a plurality of times are not similar to within a few percent. Further, a plurality of times means that the same measurement of for example, voltage is repeated, for example, 10 or 20 times.

Conventionally, optimization of the wait time is repeatedly made by human operation, by selecting the testing items for the optimization of the wait time and confirming data values following a change in the wait time.

In recent times, however, the number of items tested of the semiconductor device have enormously increased, thus much more time is needed in optimization operations on resultant wait times. These items include DC and AC measurement, function

tests, etc. Various kinds of DC measurement are performed, and for each one the input signal value is varied, thus inevitably increasing the number of items involved.

5   As is set out above, the conventional method for optimizing the semiconductor testing time takes a lot of time.

BRIEF SUMMARY OF THE INVENTION

According to a first aspect of the present

10   invention, a semiconductor testing apparatus comprises: a test program memory section for storing a test program including at least a wait time for testing a semiconductor device; a measuring/deciding section, connected to the test program memory section, for

15   receiving the test program stored in the test program memory section and applying the test program to the semiconductor device, in accordance with the test program with the wait time set to a predetermined value, and for detecting the optimal value of the wait

20   time through a series of processes comprising measuring, after elapse of the wait time, the electrical characteristics of the semiconductor device on the basis of the response signal outputted from the semiconductor device, and making an OK/NG decision on

25   the electrical characteristics of the semiconductor device on the basis of the measurement results and, if the decision is "NG", remeasuring the electrical

characteristics of the semiconductor device under a
newly set wait time and, for each newly set wait time,
performing the remeasuring operation on the electrical
characteristics of the semiconductor device until the
result of the decision is "OK" and initiating the next
measuring when the result of the decision is "OK"; and
a wait time initializing/changing control section,
connected to the measuring/deciding section, for
receiving the result of the decision by the
measuring/deciding section after the initialization of
the wait time included in the test program and
controlling the measuring/deciding section to, if the
result of the decision is "NG", repeat the setting of
the wait time in a manner to sequentially increment the
wait time toward an initially determined maximal value
until the result of the decision is "OK" and, if the
result of the decision is "OK", terminate the setting
of the wait time.

According to a second aspect of the present
invention, a method for testing a semiconductor device
includes the steps of preparing a semiconductor device
as a testing target; setting a wait time to an
initialized value; supplying a test signal to the
semiconductor device and, upon receipt of a response
signal outputted from the semiconductor device in
accordance with the test signal after an elapse of
the initialized wait time, measuring the electrical

characteristics of the semiconductor device; effecting

an OK/NG decision on the semiconductor device in

accordance with the result of measurement; if the

result of the decision is found to be "NG", effecting

5   a repeated setting of a wait time such that, until

the result of the decision is "OK", the wait time is

sequentially incremented from the initialized value

toward an initially determined maximal value; and

terminating the setting of the wait time if the result

10   of the decision is "OK".

BRIEF DESCRIPTION OF THE SEVERAL VIEWS OF THE DRAWING

FIG. 1 is a block diagram showing an arrangement

of a semiconductor testing apparatus according to

a first embodiment of the present invention;

15   FIG. 2 is a flow chart showing a wait time

optimizing method of a first aspect carried out by the

use of the semiconductor testing apparatus of FIG. 1;

FIG. 3 is a flow chart showing a wait time

optimizing method of a second aspect carried out by the

20   use of the semiconductor testing apparatus of FIG. 1;

FIG. 4 is a block diagram showing an arrangement

of a semiconductor testing apparatus according to a

second embodiment of the present invention;

FIG. 5 is a flow chart showing a wait time

25   optimizing method of a first aspect carried out by the

use of the semiconductor testing apparatus of FIG. 4;

and

FIG. 6 is a flow chart showing a wait time optimizing method of a second aspect carried out by the use of the semiconductor testing apparatus of FIG. 4.

DETAILED DESCRIPTION OF THE INVENTION

5   The embodiments of the present invention will be described in more detail below by referring to the accompanying drawing.

   FIG. 1 shows an arrangement of a semiconductor testing device according to a first embodiment of the

10 present invention.

   In FIG. 1, a test program for testing a semiconductor device 11 as a testing target is stored in a test program file 12. The test program which is stored in the test program file 12 is supplied to

15 a measuring device 13. Based on the test program a test input signal is supplied to the semiconductor device 11 by the measuring device 13. An output signal of the semiconductor device 11 is received by the measuring device 13. The characteristics of the

20 semiconductor device 11 are measured by the measuring device 13 in accordance with this output signal. The measurement by the measuring device 13 is carried out each time a wait time previously stored in the test program file 12, that is, a wait time from the supply

25 of the test input signal to the semiconductor device 11 until the output signal of the semiconductor device 11 becomes stable, is set to a predetermined value.

The wait time, though differing dependent upon the kind of semiconductor device 11, is typically of the order of 1 to a few hundreds of ms.

A deciding section 14 decides the result of measurement by the measuring device 11 and controls the measuring device 11 such that, if the result of the decision is "OK", then measurement is shifted to the next test item. If the result of the decision is "NG", control is passed over to a wait time change control section 15. The optimal value of the wait time is detected by the wait time change control section 15. Upon a decision by the deciding section 14, a wait time adjusting flag is stored, as required, in a wait time adjusting flag memory section 16 and, in a subsequent decision, reference is made to the wait time adjusting flag.

The wait time change control section 17 effects control such that, until the result of the decision section 14 is "OK", a new wait time is set in accordance with a predetermined sequence. Upon control, as required, data on the wait time is referred to after being stored in the wait time memory section 17. With reference to the above-mentioned sequence, a semiconductor test time optimizing method will be set forth in more detail below in connection with the first and second embodiments.

The initial wait time value stored in the wait

time memory section 17 is set by a wait time
initializing section 18.

That is, the semiconductor testing apparatus of
FIG. 1 has, as a basic structure, a measuring/deciding
section including the measuring device 13 and deciding
section 14 and a wait time initializing/changing
control section including the wait time change control
section 15 and wait time initializing section 18.

The measuring/deciding section measures the
electrical characteristics of the semiconductor device
11 under a condition that the wait time stored in the
test program file 12 is set to a predetermined value,
and decides the result of such measurement that, if the
result of the decision is found to be "NG", remeasuring
is carried out under a newly set wait time and, until
the result of the decision is "OK", such remeasuring is
carried out each time the wait time is newly set.
Through a series of such processes, the optimal wait
time value is detected. The measuring/deciding section
functions to shift the measurement to the next testing
item if the result of decision is "OK".

The wait time initializing/changing control
section has the following functions (a) or (b).

(a)   First, all the wait times stored in
the test program file 12 are initialized to 0 ms and,
if, after this, the result of the decision by
the measuring/deciding section is found to be "NG",

the wait time is gradually incremented in a repeated
setting toward an initially determined maximal value,
until the result of decision is "OK", and the setting
of the wait time is terminated if the result of the

5   decision is "OK".

(b)   First, all the wait times stored in the test
program file 12 are initialized to an initially
determined maximal value and, unless the result of the
decision by the measuring/deciding section becomes "OK"

10   and the wait time adjusting flag is set to an ON state,
the wait time is gradually decremented toward 0 ms.
If the result of the decision is found to be "NG", the
wait time adjusting flag is set to an ON state and then
the wait time is gradually incremented in a repeated

15   setting toward the initially determined maximal value
until the result of decision becomes "OK". If the
result of the decision becomes "OK" and the wait time
adjusting flag is set to an ON state, then the setting
of the wait time is terminated. An incrementing or

20   decrementing rate is, for example, about 10% of any
determined wait time.

FIG. 2 shows a flow chart of a wait time
optimizing method of a first aspect using the
semiconductor testing apparatus of FIG. 1.

25   This optimizing method is adapted to detect an
optimal wait time by first initializing the wait time
to 0 ms and gradually incrementing the wait time, and

this is performed in the steps explained below.

At Step 1, all the wait times stored in the test program file 12 are initialized to 0 ms.

At Step 2, the characteristics of the semiconductor device 11 are measured and, at Step 3, the result of the measurement is based on the decided value. If the result of the decision is "NG", then it is decided whether or not the wait time reaches an initially determined maximum value MAX (Step 4). If the maximum value MAX is not reached, then the wait time is incremented by, for example, about 10% of any determined wait time (Step 5) and control is returned again back to Step 2 and the characteristics of the semiconductor device 11 are measured. If the result of the decision becomes "OK" at Step 3, then a shifting is made to the next measurement.

The decision value used at Step 3 is an average value $\pm a\delta$ (a is arbitrarily designated) of a plurality of measured values obtained under a wait time of an initial value before adjustment. The decision value is calculated after the start of testing. It may be possible to initially obtain an average value $\pm a\delta$ before adjustment. In this case, the decision value is calculated from a measuring value file before the start of testing.

In the first embodiment using the semiconductor test time optimizing method, a series of measuring,

deciding and wait time incrementing processes is
performed until all the measurements are completed.

FIG. 3 shows a flow chart of a wait time
optimizing method using a semiconductor testing
apparatus according to a second aspect of the present
invention.

This optimizing method sets a wait time to
an optimal value by first initializing a wait time to
a maximal value MAX and then gradually decrementing
the wait time. This is performed at steps as set out
below.

As Step 1, all the wait times stored in the test
program file 12 are initialized to an initially
determined maximal value MAX.

At Step 2, the characteristics of the
semiconductor device 11 are measured and, at Step 3,
decision is made based on the result of the
measurement. If the result of the decision is "OK",
then it is decided whether or not a flag stored in
the wait time adjusting flag memory section 16 is set
to an ON state (Step 4). If the flag is not set to
an ON state, then it is decided whether or not the next
wait time is 0 ms (Step 5). If the wait time is not
0 ms, the wait time is decremented by, for example,
about 10% of any determined wait time (Step 6) and
control goes back to Step 2 again to measure the
characteristics of the semiconductor device 11.

Where, at Step 4, the wait time adjusting flag is
decided as being set to an ON state and, at Step 5, the
wait time is decided as being 0 ms, a shifting is made
to the next measurement.

5   If, at Step 3, the result of the decision is found
to the "NG", then a flag stored in the wait time
adjusting flag memory section 16 is set to an ON state
at Step 7. Then at Step 8, it is decided whether or
not the wait time reaches the initially determined
10   maximal value MAX. If it reaches the maximum value
MAX, a shifting is made to the next measurement.
If, on the other hand, it does not reach the maximal
value MAX, the wait time is incremented by about 10% of
any determined wait time (Step 9) and control goes back
15   to Step 2 again to measure the characteristics of the
semiconductor device 11.

Even in this case, a decision value used at Step 3
is an average value $\pm a\delta$ (a is arbitrarily designated)
obtained from a plurality of measured values under
20   a wait time of an initial value before adjustment.
The decision value is calculated after the start of
testing. It may be possible to initially obtain an
average value $\pm a\delta$ before adjustment. In this case,
the decision value is calculated from the measuring
25   value file before the start of testing.

In the second aspect of a semiconductor testing
time optimizing method, a series of measuring, deciding

and wait time incrementing or wait time decrementing processes is performed until all the measurements are completed.

According to the above-mentioned semiconductor testing apparatus and semiconductor test time optimizing method, the optimized value of the wait time is automatically detected, while measuring the electrical characteristics of the semiconductor device. By doing so, the wait time is optimized and it is, therefore, possible to reduce the time required for the optimization of the wait time when compared with the conventional optimization method.

FIG. 4 shows an arrangement of a semiconductor device according to the second embodiment of the present invention. The same reference numerals are employed in this embodiment to designate parts or elements corresponding to those of the semiconductor testing apparatus according to the first embodiment shown in FIG. 1.

A measuring control apparatus 20 controls a measuring control device 13 and includes a measuring data memory section 21, a number of measurements counting section 22, a number of measurements deciding section 23, a calculating section 24 and a stable state deciding section 25.

A wait time calculating section 26 calculates a wait time based on an output from the measuring

control apparatus 20. The wait time which is
calculated by the wait time calculating section 26 is
stored in a wait time memory section 17.

The measuring control apparatus 20 effects control
5 such that the measuring device 13, measuring data
memory section 21, number of measurements counting
section 22, number of measurements deciding section 23,
calculating section 24 and stable state deciding
section 25 perform processing in accordance with
10 a predetermined measuring processing loop. Further,
the measuring control apparatus 20 allows them to exit
from the measuring processing loop when the result of
the decision by the stable state deciding section 25 is
found to be "OK" and passes the control over to the
15 wait time calculating section.

FIG. 5 is a flow chart showing one aspect of
a wait time detection method using the semiconductor
testing apparatus of FIG. 4.

In this wait time detecting method, if the test
20 measuring condition is set by the measuring device 13
on the basis of a test program stored in the test
program file 12 (Step 1), measuring is immediately
started by the measuring device 13 and it is repeatedly
performed. The results of the measurements are
25 sequentially stored as a data array in the measuring
data memory section 21 and the number of measurements
counting section 22 counts the number of measurements,

i, (i = a positive integer of 1 or more). When the number of measurements, i, reaches the calculation target number of measurements, j, (j = a positive integer of 1 or more), calculation is performed on a j number of data arrays thus far obtained by the j number of measurements, that is, performed on the data arrays by the calculating section 24 based on a statistical procedure, and analysis is made in realtime. The state of the measuring data is decided by the stable state deciding section 25 from the result of the analysis by the calculating section 24. If the result of the decision is found to be "NG", the number of measurements, i, are stepped up and control is passed once more to remeasurement. By doing so, further analysis is again made on a new data array in realtime based on the statistical procedure and the stable state of the measuring data is again decided. The remeasurement, reanalysis and redecision are repeated until the result of the decision becomes "OK" or i reaches a maximum number of measurements, k (> j), - Step 2.

When the result of the stable state decision becomes "OK" and control is passed, then the wait time calculating section 26 calculates a real measuring time corresponding to the number of measurements, i, and obtains an optimal value of the wait time (Step 3). Here, upon calculating the real measurement time

corresponding to the number of measurements, i, it is possible to readily calculate it, for example, as a once real measuring time $\Delta t \times i$ = wait time. The calculated real measuring time is stored in the wait time memory section 17 (Step 4).

The above-mentioned Step 2 comprises a Step 2-1 for deciding whether or not the measuring number of steps, i, reaches a calculation target number of measurements, j, a Step 2-2 for effecting analysis by performing calculation on a j number of data arrays, a Step 2-3 for deciding the stable state of the measured data from a result of analysis and a Step 2-4 for stepping a measuring number of steps, i, to effect one remeasuring control.

FIG. 6 is a flow chart showing one practical example of a measuring processing loop by the measuring control apparatus 20 on the semiconductor testing apparatus of FIG. 4.

This measuring processing loop is carried out by the steps as set out below.

At Step 1, the number of measurements, i, is set to 1 and measuring means [i] is started and measuring data is stored (Step 2). At Step 3, it is decided whether or not i reaches the calculation target number of measurements, j. Where a result of the decision is found to be "NG" (i < j), i is stepped up by one (i is calculated) at Step 4. Thereafter, control again goes

back to Step 2 and the measuring means [i] is
repeatedly performed and the result of the measurement
is stored as a data array in the measuring data memory
section 21.

5   Where, at Step 3, the result of the decision on
the number of measurements, i, is found to be "OK"
($i \geqq j$), it is decided whether or not the number of
measurements, i, is less than a maximal number of
measurements, k (> j), - Step 5. When the result of
10   the decision is found to be "OK" (i < k), then on a j
number of data arrays so far obtained by the number of
measurements, j, analysis is made in realtime by the
calculating section 24 based on the statistical
procedure and calculation is made on a data value Dcp
15   including a process capability cp or cpk of the j
number of data - Step 6.

And it is decided whether or not the data value
Dcp is less than a limit value LIMIT and the stable
state of the measuring data is decided - Step 7.
20   When the result of the decision is found to be "OK"
($Dep \geqq LIMIT$), control exits from the measuring
processing loop. When the result of the stable state
decision is found to be "NG" (Dcp < LIMIT), i is
stepped up by 1 and remeasuring means [i] control is
25   carried out once - Step 8. After this, it is again
decided whether or not i is less than the maximal
number of measurements, k, - Step 5. When the result

of the decision at Step 5 is found to be "NG" ($i < j$),
then Dcp calculation and stable state decision are
suspended and control exits from the measuring
processing loop. That is, when the result of

5 the stable state decision is found to be "NG"
(Dcp < LIMIT), remeasuring is carried out and, on a new
data array, reanalysis is made in realtime based on the
statistical procedure, and redecision is made on the
stable state of the measuring data. The remeasuring,

10 reanalysis and redecision are repeatedly carried out
until the result of the decision is "OK" or i exceeds
the maximal number of measurements k ($> j$).

In the semiconductor testing apparatus shown in
FIG. 4, the result of calculation by the wait time

15 calculating section 26 is stored in the wait time
memory section 17 and the function of performing
automatic optimization control of the wait time of the
test measuring condition based on the stored contents
is imparted to the measuring control apparatus 20, so

20 that the wait time can be automatically optimized.

The measuring control apparatus 20, number of
measurements counting section 22, number of
measurements deciding section 23, calculating
section 24, stable state deciding section 25 and wait

25 time calculating section 26 may each be constructed by
dedicated hardware, or at least parts of these can be
softwarized with the use of a CPU.

According to the semiconductor testing apparatus
and semiconductor test time optimization method shown
in FIGS. 4 to 6, it is possible to automatically detect
the optimal value of the wait time while measuring the

5   electrical characteristics of the semiconductor device.
Since the wait time can be optimized based on the
detection results, the time required for optimization
of the wait time can be reduced, when compared with
the conventional optimization method.

10   Additional advantages and modifications will
readily occur to those skilled in the art. Therefore,
the invention in its broader aspects is not limited to
the specific details and representative embodiments
shown and described herein. Accordingly, various

15   modifications may be made without departing from the
spirit or scope of the general inventive concept as
defined by the appended claims and their equivalents.